ZWO

FF131 APO

■ 使用说明书

警告

请勿通过本望远镜直接观测太阳，这样做可能导致瞬间失明，请购买专用太阳观测滤镜或滤膜，来获得最安全的观测指导。

www.zwoastro.cn

中文版（简体）

使用产品前请仔细阅读本使用说明书

FF131 APO 是一款口径为 131 毫米，焦距为 983 毫米，原生焦比为 F7.5 的天文摄星镜，用途多样，兼顾目视观测与天文摄影。

该望远镜采用前三后一的四片式光学结构，内含一片 ED 玻璃，并支持全面幅拍摄。采用自平场设计，连接相机等成像配件后，仓焦即可直接拍摄（含焦距指南 M54-M48 拍摄接口端面算起，后镜连接有效长度为 42mm-73mm 即可合焦）。

遮光罩采用可伸缩式设计，能进一步缩减整体长度，提升便携性。镜筒整体采用高质量 CNC 工艺加工，内部设有光阑，可有效抑制杂散光。

把手处预留寻星镜基座槽，调焦器两侧亦各配备一个寻星螺基座，不仅便于灵活调整寻星镜位置而无需拆卸，也为安装其他天文配件提供了更多可能。拍摄使用 CNC 定制手拧螺丝搭配标亮式开口设计，无需多余工具，拆卸方便。

FF131 APO 配备 3 英寸齿轮齿条式双速调焦器，支持 1:10 的精密调焦。后端集成 360度像场旋转器，便于精确构图。鸠尾板为 300 毫米标准宽版规格，多孔位设计便于调整安装位置。

镜筒末端提供 2 英寸与 1.25 英寸接口，方便接驳各类附件。此外，FF131 APO 还标配四段式摄影延长筒，内含 2 英寸滤镜螺纹，后端配备 M48×0.75 与 M54×0.75 规格的摄影接环，以满足多样化的拍摄需求。

FF131 APO 规格


有效口径： 131mm
焦距： 983mm
焦比： F7.5
物镜类型： 四片式全分离APO（包括一片ED玻璃）
成像圈： 44mm


调焦筒缩进状态下后端最长连接长度：
拍摄模式：
73mm（从M48×0.75外螺纹算起）
91mm（从M54×0.75外螺纹算起）
观测模式：
131mm（从1.25英寸接口算起）
141mm（从2英寸接口算起）

调焦筒伸出状态下后端最短连接长度：
拍摄模式：
42mm（从M48×0.75外螺纹算起）
60mm（从M54×0.75外螺纹算起）
观测模式：
100mm（从1.25英寸接口算起）
110mm（从2英寸接口算起）


全长：
878mm（含1.25英寸接口缩进状态） 963mm（含1.25英寸接口伸长状态）
941mm（加拍摄接口缩进状态） 1026mm（加拍摄接口伸长状态）
OTA重量： 7.9kg
总重（包含镜手、附圈和鸠尾板）： 9.4kg
末端接口： (1) M78×1- 55MM 延长环
(2) M78×1 - M54×0.75
(3) M54×0.75 - M54×0.75
(4) M54×0.75 - M48×0.75 (内置 M48×0.75 滤镜螺纹)

产品尺寸及部件图






调焦器锁紧螺丝示意图





目视模式




拍摄模式


M54-M48拍摄接口端面算起，后端连接有效长度为42mm-73mm即可合焦







包装含有



FF131 APO本体一个，照顾一对，提手一个，300mm罕版鸠尾板一个，标配四段式摄影延长管

说明书



保修卡

检测单

官方网站 微信公众号 视频号

哔哩哔哩 小红书 抖音

FF131 APO

■ User Manual

WARNING

DO NOT LOOK AT SUN THROUGH TELESCOPE.
IT WILL CAUSE IRREVERSIBLE DAMAGE TO YOUR EYE.

www.zwoastro.com

English

Please read this user manual carefully before using the product.

The FF131 APO is an OTA with an aperture of 131mm, a focal length of 983mm, and a native focal ratio of F7.5. It is designed for both visual observation and astrophotography.

The telescope features a quadruplet optical lens design (three elements in the front and one in the rear), including one piece of ED glass, which can effectively reduce chromatic aberration, and supports 44mm full-frame imaging. With its self-flattened design, after attaching the imaging accessories, users can directly use it for shooting after the OTA is in focus. (The effective back focus is measured from the M54–M48 imaging interface flange. Focus can be achieved when the total rear connection length is between 42 mm and 73 mm).

The retractable dew shield helps reduce overall length and improves portability. The entire lens tube is manufactured using high-quality CNC machining and paint finish, and it also includes an internal baffle to effectively suppress stray light.

On the handle bar of FF131 APO, it has a finder base slot. Besides, there are two finder bases on both sides of the focuser. This allows flexible adjustment of the finder scope position without disassembly and provides additional options for attaching other astronomical accessories. The tube rings feature CNC-machined thumb screws and a clamshell opening design, enabling tool-free installation and removal.

The FF131 APO comes with a 3-inch rack-and-pinion dual-speed focuser offering 1:10 fine adjustment, along with a built-in 360° field rotator at the rear for precise framing. It includes a 300mm standard Losmandy-style dovetail plate with multiple holes, which makes it easy to adjust the position.

The rear interface of the FF131 APO includes both 2-inch and 1.25-inch adapters, enabling compatibility with a wide range of astronomical accessories.

The FF131 APO comes standard with Standard Four-Section Extension Tube, which includes M48*0.75 and M54*0.75 adapters. It also features a built-in 2-inch filter thread for easy attachment of filters.

FF131 APO Specifications:

Aperture size: 131mm
Focal length: 983mm
Focal ratio: F7.5
Objective lens: Quadruplet air-spaced APO（including one ED glass）
Image circle: 44mm


Maximum allowable optical path length （with the focuser fully retreated）:
Imaging Mode:
73mm (from the base of M48×0.75 male thread)
91mm (from the base of M54×0.75 male thread)
Visual Mode
131mm (from the end of 1.25" eyepiece holder)
141mm（from the end of 2" eyepiece holder)


Minimum allowable optical path length（with the focuser fully extended）:
Imaging Mode:
42mm (from the base of M48×0.75 male thread)
60mm (from the base of M54×0.75 male thread)
Visual Mode:
100mm (from the end of 1.25" eyepiece holder)
110mm (from the end of 2" eyepiece holder)


Total length:
878mm（including 1.25" adapter as dew shield contracted）
963mm（including 1.25" adapter, fully stretched）

941mm（including the photographic extension tube as dew shield contracted）
1026mm（including the photographic extension tube, fully stretched）
Net weight: 7.9kg
Gross weight（including tube ring&dovetail plate）: 9.4kg
Rear-end thread type:
(1) M78×1 - 55MM adapter
(2) M78×1 - M54×0.75
(3) M54×0.75 - M54×0.75
(4) M54×0.75 – M48×0.75 (with built-in M48×0.75 filter thread)


Product Overview and Dimensional Diagram








The Locking Screw Position Diagram




② Bottom Load Adjustment Screw
③ Bottom Locking Screw
①②④⑤ Can be used for electric focusing bracket installation

Visual Mode




Imaging mode


The effective focus range of the telescope rear-end connection is from 42 mm to 73mm (from the M54 to M48 photographic adapter).




Steps of Installing EAF




① Use a 2mm wrench to loosen the screw and remove the coarse adjustment knob



② Put the motor bracket on and screw the standard M4 screws into the hole shown, but please do not lock them now.



③ Choose the 6mm flexible coupling and lock this screw.



What's in the box



FF131 APO main unit ×1
Carrying Handle ×1
300 mm Narrow Dovetail Plate ×1
Tube Rings ×1 pair
Standard Four-Section Extension Tube

User Manual



Warranty card



Inspection Certificate

Official site Facebook YouTube

Ins Twitter